

MyHOME® Radio

Radio loads selection chart

Switches and dimmers maximum loads at 230 V~ (for values at 110 V~, please halve values)

		Leading edge		Trailing edge		Universal			
		Incandescent lamp Halogen lamp	ELV halogen with ferromagnetic transformer	ELV halogen with electronic transformer	Fluorescent tube	Compact fluorescent bulb	LED bulb	LED or Fluorescent lamps with 1-10 V ballast	Reducer motor for roller blind
Cat.Nos									
SWITCHES	0 672 33	2500 W	2500 VA	2500 VA	1250 VA	1250 VA	1250 VA	-	-
	0 672 34	2 x 1000 W	2 x 1000 VA	2 x 1000 VA	2 x 500 VA	2 x 500 VA	2 x 500 VA	-	-
	5 735 45	3 x 1000 W	3 x 1000 VA	3 x 1000 VA	3 x 500 VA	3 x 500 VA	3 x 500 VA	-	-
	0 672 63	-	-	-	-	-	-	-	500 VA
	0 883 26	-	-	-	-	-	-	-	460 VA
	5 738 62	2500 W	2500 VA	2500 VA	1250 VA	1250 VA	1250 VA	-	-
	0 883 39	2500 W	2500 VA	2500 VA	1250 VA	1250 VA	800 VA	yes	-
	5 738 60	2 x 2500 W	2 x 2500 VA	2 x 2500 VA	2 x 1250 VA	2 x 1250 VA	2 x 1250 VA	yes	-
	0 883 06	300 W	250 VA	250 VA	150 W	150 W	100 W	-	-
	0 883 23/33	2500 W	2500 VA	2500 VA	-	1250 W	1250 W	-	-
DIMMERS	0 695 03	2500 W	1250-2500 VA	1250-2500 VA	1250 W	1250 W	1250 W	-	-
	0 672 27	7 W - 300 W	35 VA - 300 VA	10 VA - 300 VA	-	9 W - 60 W dimmable fluocompact	5 W - 60 W dimmable LED	-	-
	5 735 46	600 W	450 VA	600 VA	-	-	-	-	-
	5 735 48	-	-	-	-	-	-	1000 VA	-
	5 738 66	-	-	-	-	-	-	1000 VA	-
	5 738 64	600 W	450 VA	600 VA	-	-	-	-	-
	0 883 20	50 W-500 W	60 VA-500 VA	60 VA-500 VA	-	-	-	-	-
	0 883 34	7-300 W	35-300 VA	0-300 VA	-	9-50 W Dimmable fluocompact	5-60 W Dimmable LED	-	-

Local and remote control by Legrand APP

